



## PA2-KIT

PA2-KIT is an accessory package for FANVIL SP Intercom/Paging Gateway PA2. It includes IP camera module, speaker module, microphone module and button module. You can quickly build high quality audio/video intercom equipment by PA2-KIT, eliminating the components selection, matching test and reliability test cumbersome process.



PA2-KIT

## <u>High</u>lights

 $\checkmark$  High reliability components, plug and play

- 720P camera module to achieve HD video call; The lens mounting height and Angle can be adjusted to meet the requirements of various scenarios
- 🖾 High sensitivity pick up, waterproof, dustproof designed microphone module, suitable for harsh environment application
- $\boxed{}$  5W/8  $\Omega$  speaker module, satisfied the noisy environment to the demand of the high loudness of the intercom equipment
- $\ensuremath{\square}$  Waterproof and dustproof designed stainless steel button with LED indicator for better operation

Component	Photo	Functions	Features		
Speaker		<ul> <li>Speaker with self-adhesive layer.</li> <li>Module with dustproof, waterproof protective film.</li> <li>5W/8 Ω Waterproof loudspeaker.</li> </ul>	5W/80 Waterproof loudspeaker. The diameter of the horn is 57mm and 13.7mm high Include 150cm Shielding wire.		
Microphone		<ul> <li>Microphone with self-adhesive layer.</li> <li>Module with dustproof, waterproof protective film</li> <li>The sensitivity of microphone is -38dB ± 2.</li> </ul>	Sensitivity:-38dB $\pm$ 2, Standard working voltage: 3V, the maximum working voltage is 10V, Output impedances $\leq 2.2$ K $\Omega$ , Diameter of the microphone is 9.7mm and the height is 4.7mm. Include 150cm Shielding wire.		
Button		<ul> <li>Stainless steel button with backlight.</li> <li>Protect level IP67, IK10.</li> <li>The mechanical lifetime of the button is 200,000 times.</li> <li>LED lamp lifetime is 400,000 hours.</li> </ul>	The diameter of the button is 16mm and the height is 23.8mm. The button is self-restorable stainless steel button with 150cm shielding wire.		
IP Camera		<ul> <li>Module with self-adhesive layer</li> <li>720P HD camera, support dual video stream</li> <li>Power by PA2 LAN Port (12V DC)</li> <li>Wide angle lens, the installation angle can be fine tuned</li> <li>NOTE: Do not connect the POE injector /switch directly using this camera module. It will be damaged</li> </ul>	1. 0M 1/4"H62 CMOS sensor color 0.1Lux@F1.2 black/white 0.01Lux@F1.2 H. 264, support dual stream, AVI Main stream: 1280*720 sub-stream: 704*576		

The above specifications may be updated in the future without prior notice. All hardware/software/physical features should be based on the final shipped products. For more information, please visit: www.fanvil.com

Compatibility List:								
<b>3</b> CX.	Asterisk	AVAYA		cepygi *	MUAWEI	Jabra GN	metaswitch	NEC
	<b>OpenVox</b> <sup>*</sup>	<b>Phon</b> ism	plantronics			<b>;</b> Yeastar	ZTE中兴	



www.fanvil.com Add: 4F, Block A, Building 1#, GaoXinQi Hi-Tech Park (Phase-II), 67th District, Bao'An, Shenzhen, 518100, China Tel: +86-755-2640-2199 Fax: +86-755-2640-2618 Email: sales@fanvil.com